



**DESIGN AND DEVELOPMENT OF MICROWAVE
ABSORBER USING WASTE MATERIALS**

by

LIYANA BINTI ZAHID

(1340810919)

A thesis submitted in fulfillment of the requirement for the degree of
Doctor of Philosophy in Communication Engineering

**School of Computer and Communication Engineering
UNIVERSITY MALAYSIA PERLIS**

2017

ACKNOWLEDGEMENT

In the name of Allah, Most Gracious, the Most Merciful. All praise to Allah the Almighty, for the blessing that lead to my success in completing my research.

I would like to express my gratitude and sincere appreciation to my PhD lead supervisor, Dr. Muzammil Bin Jusoh for his continuous encouragement, extensive support, freedom and trust that enabled this research to run smoothly. Without his guidance and persistent help, this thesis would not have been possible. Special thanks to Prof Dr. Mohd Fareq Bin Abd Malek, Dr Cheng Ee Meng and Dr Liu Wei Wen for their constant guidance and encouragement . I would like to thank Dr. Lee Yeng Seng for all his help and guidance throughout my research. A bunch of thanks go to all of my colleagues at Advanced Microwave Research Laboratory (AMREL), UniMAP, Perlis for the help, guidance and friendly environment including Dr. Nazri, Baizatul, Hui Fang, and Shafiq. For their unwavering support, I am truly grateful. Finally, my deep, sincere gratitude and special thanks to my family especially to my parents Zahid Bin A. Bakar and Norazlina Binti Shariffuddin, my lovely sisters Munirah and Najihah and my youngest brother, Ahmad Nazmi for their continuous and unparalleled love, help and unconditional support. I am grateful to have them by my side throughout this journey. And most of all for my loving, supportive and encouraging husband, Kamarul Aizat Bin Abdul Khalid who's always cheering me up and your faithfully support during the final stage of this PhD,it is much appreciated. It is all due to their prayers, patience and understanding that have driven me to this extends. Thank You.

Liyana Binti Zahid

TABLE OF CONTENTS

	PAGE
DECLARATION OF THESIS	i
ACKNOWLEDGEMENT	ii
TABLE OF CONTENTS	iii
LIST OF FIGURES	vii
LIST OF TABLES	xii
LIST OF ABBREVIATIONS	xiv
LIST OF SYMBOLS	xvi
ABSTRAK	xvii
ABSTRACT	xviii
CHAPTER 1 INTRODUCTION	
1.1 Background	1
1.2 RF/ Microwave Absorber	2
1.3 Problem statement	4
1.4 Objectives of Project	6
1.5 Scopes of Project	6
1.6 Thesis Organization	7
CHAPTER 2 LITERATURE REVIEW	
2.1 Overview	9

2.2	Anechoic Chamber	10
2.3	Microwave Absorber Properties	12
2.3.1	Dielectric Constant	12
2.3.2	Wavelength	13
2.3.3	Loss Tangent	14
2.4	RF Absorber (Microwave Absorber)	14
2.4.1	Investigation of Waste Materials	17
2.4.2	Absorber Types	23
2.5	Evaluation of EMC Absorber	25
2.5.1	Setup and Model of the Measurement	25
2.5.2	Dielectric Properties Measurement	26
2.5.3	Dielectric Probe Technique	27
2.6	Transmission and Reflection Measurement	30
2.7	Reflectivity Measurement	30
2.8	Summary of the Work	32
2.9	Summary	39
 CHAPTER 3 RESEARCH METHODOLOGY		
3.1	Introduction	40
3.2	Dielectric Properties Measurement	42
3.2.1	Materials and Sample Preparation	42
3.2.2	Transmission Line Measurement	45
3.2.3	Coaxial Probe Measurement	47
3.2.4	Calibration Procedure	49
3.3	Material Properties Investigation	52

3.3.1	Scanning Electron Microscope Image	52
3.3.2	Carbon, hydrogen, nitrogen and sulfur Analysis (CHNS)	54
3.4	Pyramidal Absorber Mold Fabrication	54
3.5	Pyramidal Microwave Absorber Fabrication	55
3.6	Flat Absorber Fabrication	57
3.7	Microwave Absorber Simulation Design in CST Microwave Studio	58
3.7.1	Simulation of 4x4 Array of Pyramidal Microwave Absorber	58
3.7.2	Simulation of the Pyramidal Microwave Absorber with Different Dimensions of Pyramidal Microwave Absorber	60
3.7.3	Simulation of Different Signal Source Distance to the Microwave Absorber	60
3.7.4	Simulation of Different Angle of Signal Source	61
3.8	Design of Geometrically Tapered Microwave Absorber	61
3.8.1	Parameters of The Microwave Absorber	62
3.9	Design of Serial Array of Absorber	65
3.10	Measurement of Pyramidal Microwave Absorber	67
3.11	Summary	69

CHAPTER 4 RESULT AND DISCUSSION

4.1	Introduction	70
4.2	Magnetic and Dielectric Properties of Sugarcane Bagasse (SCB), Rubber Tire Dust (RTD) and Composite of SCBRTD Samples	71
4.2.1	Magnetic Properties of SCB and RTD Samples	72
4.2.2	Dielectric Properties	74
4.2.3	Dielectric Properties of Sugarcane Bagasse and Rubber tire Dust	74

4.2.4	Effect of Rubber Tire Dust Filler into Sugarcane Bagasse on Dielectric Properties	85
4.2.5	Wave Attenuation Constant and Depth of Penetration	89
4.2.6	Phase Constant	94
4.2.7	Characteristic Impedance of the Composite of Sugarcane Bagasse and Rubber Tire Dust	96
4.3	Single Layer Sugarcane Bagasse Microwave Absorber Design	99
4.4	Two Layers Absorber	103
4.5	Numerical Study	106
4.5.1	Simulation result of sugarcane bagasse pyramidal microwave absorber	106
4.5.2	Different Dimensions	107
4.5.3	Different Distances of the Signal Source	110
4.6	Pyramidal absorber	113
4.6.1	Sugarcane Bagasse Pyramidal Absorber with Different Base	115
4.6.2	Rubber Tire Dust (RTD) Pyramidal Microwave Absorber	117
4.6.3	Geometrically Tapered (pyramidal) Shape of Different Filler Loading of SCB and RTD	119
4.7	Summary	122
CHAPTER 5 CONCLUSIONS		
5.1	Conclusion	123
5.2	Future Work	127
REFERENCES		128
APPENDICES		136
APPENDIX-A: Publications		136
APPENDIX-B: Research Awards		137

LIST OF FIGURES

NO.		PAGE
2.1	Principle of Quarter Wavelength Absorber	15
2.2	Pyramidal Microwave Absorber. (a) TDK <i>ICT 030</i> Pyramidal Microwave Absorber (TDK, 2008).(b) Eccosorb <i>VHP-8-NRL</i> Pyramidal Microwave Absorber (Emerson, 2008)	16
2.3	Agricultural waste (a) Rice Husk (b) Rice Straw (c) Sugarcane Bagasse	21
2.4	Microwave absorber (a) Rice Husk Microwave Absorber (Nornikman et al., 2010), (b) Urethane foam loaded with carbon (Eccosorb, 1973), (c) TDK ICT 030 absorber loaded with carbon plus nonflammable material (TDK, 2008)	24
2.5	The dielectric probe technique .The Agilent Technologies 85070E Dielectric Probe Kit with the high temperature probe kit	29
2.6	The display results on the chart form and table form or both (Agilent, 2011)	29
2.7	Free Space Measurement Setup.(a) Free-space insertion loss method (Cuming, 2013).(b) An NRL Arch for millimeter wave measurements	32
3.1	Flow chart of the research methodology for the optimization of the EMC absorbers.	41
3.2	The Composite that contains filler and binder	43
3.3	a) Sugarcane bagasse was being separated from its thick stem b) The sugarcane bagasse was cut into small portion c) The grinded Sugarcane bagasse	44
3.4	The fabricated samples	45
3.5	Dimension of the sample.	46
3.6	Illustrating of Transmission Line Technique using Waveguide.	47
3.7	The high temperature probe with the shorting block for the dielectric measurement setup	48
3.8	Block diagram of the experimental setup	48

3.9	Complex permittivity of water	50
3.10	Complex Permittivity of air	51
3.11	SEM Image of Sugarcane Bagasse	52
3.12	SEM Image	53
3.13	The mold of pyramidal microwave absorber	55
3.14	Microwave Absorber Fabrication Tools. a) WD40. b) Sugarcane bagasse is weighted. c) Polyester resin is weighted using electronic scale	56
3.15	The process of microwave absorber fabrication. (a) The transparency plastic is placed into the absorber mold, (b) The mixture needed to be compacted in the absorber mold, so manually pressed, (c) the mixture in the absorber mold	56
3.16	The sugarcane pyramidal microwave absorber in the mold	57
3.17	The process of making the particle board, the sugarcane bagasse mixed with polyester resin and MEKP was being mold in the particle board molder and the mold of particle board was being pressed by the steel.	58
3.18	The pyramidal microwave absorber using sugarcane bagasse	58
3.19	Dimensions of the pyramidal microwave absorber (single unit):Pyramid width, $P_w = 5$ cm, Pyramid length, $Pl = 5$ cm, Pyramid height, $Ph = 13$ cm,Base Width, $B_w = 5$ cm, Base length, $Bl = 5$ cm, Base height, $Bt = 2$ cm	59
3.20	Simulation setup for pyramidal microwave absorber using CST Microwave Studio	59
3.21	Different distances between the signal source ($d=35$ cm, $d=50$ cm and $d=65$ cm).	61
3.22	The Side View of the Pyramidal Microwave Absorber (cm)	63
3.23	The dimension of the microwave absorber in pyramidal shape	64
3.24	The interaction of Microwave signal for Geometrically Tapered PMA, showing a gradual increase in volume and loss factor along the axis of the wave propagation	65
3.25	Illustration of the interactions of the incident EM wave with a periodic array of pyramids	66
3.26	Experiment setup of reference metal plate measurement without absorber	68

3.27	Experimental setup of the bi static reflectivity method	69
4.1	Magnetic Constant for SCB, RTD and Composite of SCBRTD.	73
4.2	Magnetic Loss Factor for SCB, RTD and Composite of SCBRTD.	73
4.3	Dielectric Constant of the samples of Sugarcane Bagasse (SCB) and Rubber Tire Dust (RTD).	75
4.4	Dielectric Loss Factor of the samples of Sugarcane Bagasse (SCB) and Rubber Tire Dust (RTD)	76
4.5	Reflectivity Pure Sugar Cane Bagasse (Simulated) with different thickness from 1 mm to 6 mm	77
4.6	Reflectivity of Composite of Sugarcane Bagasse and Rubber Tire Dust with different thickness from 1 mm to 6 mm	78
4.7	Complex permittivity of sugarcane bagasse and rubber tire dust in the range frequency of 2 GHz-8 GHz	81
4.8	Complex Permittivity for sugarcane bagasse added with rubber tire dust with different composition.	83
4.9	Tangent Loss of the different Samples for Flat Layer Absorber	84
4.10	Characteristic Impedance of the different Samples for Flat Layer Absorber	84
4.11	Dielectric Constant of Different Filler of Sugarcane Bagasse and Rubber Tire Dust	87
4.12	Loss Factor of Different Filler of Sugarcane Bagasse and Rubber Tire Dust	87
4.13	Loss Tangent of Different Filler of Sugarcane Bagasse and Rubber Tire Dust	88
4.14	An illustration of wave-matter interaction and energy balance	90
4.15	Attenuation Constant and Depth of Penetration of Sugarcane Bagasse and Rubber Tire Dust	91
4.16	Attenuation Constant of Different Filler of Sugarcane Bagasse and Rubber Tire Dust	92
4.17	Depth of Penetration of Different Filler of Sugarcane Bagasse and Rubber Tire Dust	93
4.18	Phase Constant of Sugarcane Bagasse and Rubber Tire Dust	95
4.19	Phase Constant of Different Filler of Sugarcane Bagasse and Rubber	95

Tire Dust

4.20	Characteristic Impedance of Sugarcane Bagasse and Rubber Tire Dust	97
4.21	Characteristic Impedance of Different Filler of Sugarcane Bagasse and Rubber Tire Dust	97
4.22	Reflectivity of Flat Layer Absorber for SCB 1 and SCB 2 in frequency range of 3.85 GHz to 5.85 GHz	101
4.23	Reflectivity of Flat Layer Absorber for SCB 1 and SCB 2 in frequency range of 5.85 GHz to 8.2 GHz	102
4.24	Different Configuration of Absorbent Layer	104
4.25	Reflectivity performance of two-layer absorber with different arrangements of absorbing layers within range frequency of 3.85 GHz to 5.85 GHz	105
4.26	Reflectivity performance of two-layer absorber with different arrangements of absorbing layers within range frequency of 5.85 GHz to 8.2 GHz	105
4.27	Reflectivity performance of sugar cane bagasse pyramidal microwave absorber with different pyramid heights (P_h)	107
4.28	Reflectivity performance of sugar cane bagasse pyramidal microwave absorber with different base thicknesses (B_t)	109
4.29	Reflectivity performance of sugar cane bagasse pyramidal microwave absorber with different distances between the waveguide port and the absorber	110
4.30	Reflectivity performance of sugar cane bagasse pyramidal microwave absorber with different angles between the waveguide port and the absorber	112
4.31	Wave Interaction on Solid Pyramidal Microwave Absorber	114
4.32	Bi-Static, Normal Reflectivity Performance of a SCB PMA and Simulated PMA	114
4.33	Bi-Static, Normal Reflectivity Performance of a SCB PMA with Different Base Part with Reference to A Metal Plate in frequency range of 3.85 GHz to 5.85 GHz	116
4.34	Bi-Static, Normal Reflectivity Performance of a SCB PMA with Different Base Part with Reference to A Metal Plate in frequency range of 5.85 GHz to 8.2 GHz	116

- 4.35 Bi-Static, Normal Reflectivity Performance of a RTD PMA with Reference to A Metal Plate in frequency range of 1 GHz to 18 GHz 118
- 4.36 Bi-Static, Normal Reflectivity Performance of a Different Filler Loading of RTD and SCB PMA with Reference to A Metal Plate in frequency range of 1 GHz to 18 GHz 120

©This item is protected by original copyright

LIST OF TABLES

NO.		PAGE
2.1	Elemental Percentage of raw Sugarcane bagasse (Devnarain et al., 2002).	22
2.2	Previous Research of Microwave Absorber using Agricultural Waste	34
3.1	Mixing Percentage of the composition of sugarcane bagasse with rubber tire dust	45
3.2	Dimension of the samples	46
3.3	Summarization of the material properties	53
3.4	Summary Test result of CHNS Analysis	54
3.5	Parametric Study for different dimensions of the pyramidal microwave absorber	60
3.6	The parts are Pyramid Width (<i>PW</i>), Pyramid Length (<i>PL</i>), Pyramid Height (<i>PH</i>), Base Width (<i>BW</i>), Base Length (<i>BL</i>), and Base Height (<i>BH</i>)	63
4.1	Average Reflectivity of Samples of Sugarcane Bagasse in X Band and Ku Band	78
4.2	Average Reflectivity of Composite of Sugarcane Bagasse with Rubber Tire Dust	79
4.3	Mixing Percentage of the composition of sugarcane bagasse with rubber tire dust	80
4.4	Measured range of dielectric properties of the two raw materials which are sugarcane bagasse and rubber tire dust in range frequency between 2 GHz- 8 GHz	81
4.5	Measured range of dielectric properties of the three fabricated samples in range frequency between 2 GHz- 8 GHz (Composition of Sugarcane Bagasse with rubber tire dust).	83
4.6	Tangent Loss and Characteristic Impedance of the Sample Material	85
4.7	Values of Complex Permittivity and Magnitude of Normalized	93

	Impedance of the Composite of Sugarcane Bagasse and Rubber Tire Dust	
4.8	The characteristic impedance (η_m) and depth of penetration (d) values for all different filler loading at all frequencies (1 GHz to 20 GHz)	99
4.9	Different Designation of Flat Layer Absorber	101
4.10	Comparison of single layer absorber between fabricated absorber and commercializes layer microwave absorber	103
4.11	Average reflectivity performance of pyramidal microwave absorber using different pyramid heights (P_h)	108
4.12	Average reflectivity performance of pyramidal microwave absorber using different base thicknesses (B_t)	109
4.13	Average reflectivity performance of pyramidal microwave absorber using different distances between the waveguide port and the absorber, Z_{pos}	111
4.14	Average reflectivity performance of pyramidal microwave absorber using different angles between the waveguide port and the absorber	112
4.15	Different Composition of SCB and RTD	119
4.16	Summary of the work	121
5.1	EMC Performance of the Fabricated Microwave Absorber	126

LIST OF ABBREVIATIONS

2-D	Two Dimensional
BL	Back Layer
DUT	Device Under Test
EM	Electromagnetic
EMC	Electromagnetic compatibility
EMI	Electromagnetic Interferenc
FCC	Federal Communications Commission
FL	Front Layer
FSA	Free Space Arch
FSS	Frequency Selective Surfaces
GHz	Giga Hertz
GT	Geometrically Tapered
HARP	Halpern Anti Radar Paint
HFSS	High Frequency Structure Solver
HIS	High Impedance Surfaces
IFF	Identification of Friend or Foe
IL	Insertion Loss
MEKP	Methyl Ethyl Ketone Peroxide
MIL-STD	Military Standard
MUT	Material Under Test
NEMP	Nuclear Electromagnetic Pulse
NP	Null Point
OATS	Open Area Test Sites
PCB	Printed Circuit Board

PEC	Perfect Electric Conductor
PMA	Pyramidal Microwave Absorber
PVA	Poly Vinyl Acetate
RADAR	Ranging and Detection
RCS	Radar Cross Section
RH	Rice Husks
RTD	Rubber Tire Dust
RTDPMA	Rubber Tire Dust Pyramidal Microwave Absorber
SOLT	Short Open Load Thru
SCB	Sugarcane Bagasse
SCBRTD	Sugarcane bagasse rubber tire dust
TE	Transverse Electric
TM	Transverse Magnetic
TRL	Thru Reflect Load
UPR	Unsaturated Polyester Resin
VNA	Vector Network Analyzer
WLAN	Wireless Local Area Network

LIST OF SYMBOLS

ϵ_r'	Real Part of Complex Permittivity
ϵ_r''	Imaginary Part of Complex Permittivity
γ	Wave propagation constant
α	Attenuation constant
β	Phase constant
t	Thickness
Z_{in}	Input impedance
f	Frequency
dB	Decibel
Γ	Reflection coefficient
T	Transmission coefficient
Γ_1	Reflection coefficient at first interface
λ	Wavelength
l	Length of single layer absorber
θ_i	Angle of incidence
θ_r	Angle of reflection
θ_t	Angle of transmission
ϵ_r	Relative Permittivity
Z_L	Load impedance
η	Charateristic impedance
η_0	Charateristic impedance of air
ω	Angular frequency
σ_{eff}	Effective conductivity
S_{21}	Transmission S-parameter

Merekabentuk dan Membangunkan Penyerap - Penyerap Gelombang Mikro Menggunakan Bahan Terbuang

ABSTRAK

Hampas tebu tebu ialah salah satu sisa pertanian yang berpotensi untuk mereka bentuk penyerap gelombang mikro berbentuk pyramid yang diguna pakai dalam frekuensi radio (RF) bilik tak bergema untuk tujuan pengujian. Bilik anekoik RF ialah sebuah bilik berperisai yang ditutup dengan penyerap untuk menghapuskan isyarat gambaran yang tidak dikehendaki. Dalam kerja ini, hampas tebu dari sisa industri gula dan tayar getah dari industri tayar telah digunakan. Kedua-dua bahan buangan ini telah mengandungi kandungan karbon, yang telah membuat mereka sesuai seperti bahan mentah untuk rekaan penyerap gelombang mikro. Pemalar dielektrik hampas tebu tebu telah diukur menggunakan perisian Agilent dielektrik teknik dan Agilent 85071E menggunakan teknik laluan penghantaran. Penyerap gelombang mikro diperbuat daripada dua komponen utama, satu bahan yang melakukan penyerapan, dan matriks bahan mengadakan pengisi. Dalam bahan dielektrik, ciri-ciri paling genting yang membolehkan mereka digunakan seperti penyerap gelombang mikro ialah pemalar dielektrik dan faktor kehilangan yang merupakan pelepasan tenaga pada bahan tersebut. Pada umumnya, penyerap bahan dielektrik dibina oleh gabungan pengisi dalam satu matriks polimer. Dalam kerja ini, pengisi ialah sisa pertanian yang merupakan hampas tebu (SCB) tebu dan debu (RTD) tayar getah dari industri tayar manakala matriks polimer ialah Polyester Resin RP9509 (UPR) tidak tepu yang mana tegar, fleksibel dan polimer telus dalam electromagnet. Dalam kerja ini, hampas tebu tebu juga telah bercampur dengan debu (RTD) tayar getah untuk menyiasat prestasi mereka. Penyerap gelombang mikro menggunakan hampas tebu tebu telah direka dan dibuat-buat dalam perisian studio CST gelombang mikro. Ukuran teknik pandu gelombang telah digunakan untuk menyemak kehilangan (S_{11}) gelombang dan pekali penghantaran (S_{21}). Penyerap gelombang mikro sedang disiasat dalam frekuensi mikrogelombang berkisar antara 1 GHz kepada 18 GHz. Keputusan menunjukkan bahawa hampas tebu tebu mempunyai potensi sebagai bahan asas dalam memajukan penyerap gelombang mikro dan boleh beroperasi dalam gelombang frekuensi tersebut. Menambah pengisi yang merupakan debu tayar getah menambah prestasi penyerap gelombang mikro. Penyerap ini telah direka bentuk berdasarkan pengecilan gelombang dan kedalaman data penembusan dan prestasi EMC mereka dinilai dalam soal prestasi kepantulan dwi statik. Prestasi penyerap didapati menjadi di bawah -10 dB. Kepekatan berbeza pengisi diukur dan kepantulan didapati untuk memperbaiki kemudian -20dB apabila nilai bertambah debu tayar getah telah ditambah.

Design and Development of Microwave Absorbers Using Waste Materials

ABSTRACT

Sugarcane bagasse is a potential agricultural waste to design the pyramidal microwave absorber to be used in radio frequency (RF) anechoic chamber for testing application. An RF anechoic chamber is a shielded room covered with absorbers to eliminate unwanted reflection signal. In this work, sugarcane bagasse from the sugar industry and rubber tire dust from tire wear have been used. Both of the wastes have lossy carbon contents naturally, which has made them suitable as the raw materials for the fabrication of the low cost microwave absorbers. The dielectric constant of the sugarcane bagasse had been measured using the Dielectric Probe Technique and Software of Agilent 85071E using Transmission Line Technique. Microwave absorbers are made of two main components, a filler material that does the absorption, and a material matrix to hold the filler. In dielectric materials, the most crucial properties that enable them to be applicable as microwave absorbers are the dielectric constant and the loss factor which is the dissipation of energy in the material. Generally, dielectric material absorbers are fabricated by the combination of fillers in a polymer matrix. In this work, the fillers are the agricultural waste which is sugarcane bagasse (SCB) and rubber tire dust (RTD) from tire wear whereas the polymer matrix is unsaturated Polyester Resin RP9509 (UPR) which is rigid, flexible and electromagnetically transparent polymer. In this work, the sugarcane bagasse also has been mixed with rubber tire dust (RTD) to investigate their performance. The microwave absorber using sugarcane bagasse had been designed and simulated in the CST Microwave studio software. The measurement of waveguide technique has been used to check the reflectivity performance. The microwave absorber has been investigated in microwave frequency range between 1 GHz to 18 GHz. The results show that the sugarcane bagasse has the potential used as the base material in developing the microwave absorber and can operate in that range of frequency successfully. The adding of the filler which is rubber tire dust increased the performance of the microwave absorber. These absorbers were designed on the basis of the wave attenuation and depth of penetration data and their EMC performance was evaluated in terms of bi-static reflectivity performance. The performance of the absorbers was found to be below -10 dB. The different concentration of the filler were being measured and the reflectivity was found to be better than -20 dB when the increasing value of rubber tire dust were added.

CHAPTER 1

INTRODUCTION

1.1 Background

In recent years, the applications of electromagnetic compatibility (EMC) for electronic devices and equipment with different electromagnetic environments have incredibly extended the applications in GHz range for mobile phone, local area network, radar system and others (Feng, Y. B., Qiu, T., & Shen, 2007; M. S. Kim, Min, & Koh, 2009). This requires the electromagnetic compatibility (EMC) application such as microwave absorbing material in the range of frequencies from kilohertz (kHz) to gigahertz (GHz) of microwave signals. Electromagnetic interference is the degradation in the performance of device, or equipment, or a system caused by an electromagnetic disturbance. The electromagnetic disturbance can be in the nature of an electromagnetic noise, or an unwanted signal, or a change in the propagation medium itself (Kodali, 2001). At high frequency ranges, the commercialized and conventional conductive shielding materials become less effective to its function. The absorber has been used in military standard, immunity and emission test chamber (Holloway et al., 1997). The conventional conductive shielding materials include conductive foams, metal in the form of sheeting, metal flakes and stainless steel fibers in order to harness, capture and ground the EMI energy. Therefore, the EMI absorbing materials are designed. The absorber materials are created to attenuate electromagnetic wave and there is

conversion from the electromagnetic wave into heat (Ch, T E, n.d.). This design has been integrated with different loss mechanism over the broader range of bandwidths with different structures from the large thickness pyramidal structures to single layer coatings and multilayer materials. There are two categories of microwave absorber which are those that absorb incident and reflected wave energy in free space which is the empty space or vacuum. The other one is absorbers that called load, cavity and bulk loss absorbers. They absorb the waves inside waveguides and coaxial lines. Dielectric absorbers used the dielectric materials to be used as absorber application (Wang et al., 2014). Agricultural wastes such as rice husk, rice straw, coconut shells and sugarcane bagasse have their own dielectric properties and behavior. This residue agricultural waste material has potential to be used as an alternative material for pyramidal microwave absorber in Radio Frequency (RF) anechoic chamber.

1.2 RF/ Microwave Absorber

Absorbers in the RF/Microwave field are the materials to debilitate the energy in electromagnetic wave. Absorbers are used in a broad range of applications to eradicate stray or unwanted radiation that could intermeddle with a system's operation (D. Il Kim, Kim, & Choi, 2007). Absorbers can be used externally to diminish the reflection from or transmission to particular objects and can also be used internally to reduce oscillations caused by cavity resonance. They can also be used to stimulate a free space environment by eliminating reflections and bounces in an anechoic chamber. Absorbers can take many different physical forms including flexible elastomers or foam or rigid epoxy or plastics. They can be made to resist weather and temperature extremes. Absorbers have become a critical element in some systems to reduce interference

between circuit components. The interior surfaces of RF anechoic chamber are sometimes similar with acoustic anechoic chamber but there are different between these two chambers. The first absorber fabrication is 2 GHz quarter-wave resonant investigated at the Naamlooze Vennootschap Machinerieen (Naamlooze, 1936). Two materials that had been widely used for the measurement of microwave absorber are polyurethane and polystyrene. The example of microwave absorber design by using urethane foam as it based material with carbon loaded at the top of the pyramid is *VHP-8-NRL* absorber from Eccosorb (Emerson, 2008). *TDK ICT-030* absorber (TDK, 2008) is also the microwave absorber in the current market that used carbon as the material. There are two types of tests which are performed within the EMC test facilities for the compatibility of the electronic equipment and these are known as conducted and radiated EMC tests. These tests are performed in accordance with the internationally well-known standards in military and civil domains such as MIL-STD-461 and CISPR series standards (Holloway et al., 1997; Trautnitz, 2007). Active electronic components and devices in electrical, electronics and communications systems can be evaluated for their levels of emissions, radiations and sensitivity. However, microwave absorbers are passive components and are used to increase the EMC performance of the electronic systems. There are many other techniques to enhance the EMC performance such as filtering, grounding and shielding the radiated EMI.

The EMC performance of a device, system or even anechoic chamber strongly depends on the performance of the microwave absorbers which are depends on many factors, including frequency, angle of incidence, the geometry and dimension of the absorber, and the absorber reflectivity (B. Chung & Chuah, 2003). Therefore the EMC-oriented study of the microwave absorbers involves the study of all those factors that can affect its ability to control radiated EMI. The knowledge of the properties of the

absorbing material exposed to high frequency EM radiations is very important at different weight fractions of the lossy filler.

In this work, sugarcane (*Saccharum officinarum*) bagasse has been used as the main material in designing the microwave absorber. Sugarcane bagasse is a residue produced in large quantities by sugar industries. In general, 1 ton of sugarcane bagasse generates 280 kg of bagasse, the fibrous by-product remaining after sugar extraction from sugarcane (Hasnain *et al.*, 2007). Sugarcane bagasse is also the potential materials for the pyramidal microwave absorbers used in anechoic chamber to eliminate reflected signal. The large percentage of carbon that occurs naturally in sugarcane bagasse can provide good reflectivity performance (L. Huang and H. Chen, 2011). The content of carbon is the main element that helps to absorb the microwave signal.

1.3 Problem Statement

In anechoic chamber, there are four possible bounce paths, which are ceiling, floor and walls. The multipath problem at anechoic chamber is potentially much worse than an outdoor ground-plane range. Electromagnetic wave is being used in wireless communication applications and other communication equipment. This could cause the performance degradation of a device, inaccuracy of signal measurement cause by electromagnetic interference (EMI) and even can damage the component or a device. Thus, a system must be compatible within the EMI environment to control the EMI disturbance to any other device. This problem can be solved by installing the RF microwave absorbers to reduce the effect of chamber reflection to a manageable level and eliminate the interference problem of a device. Currently, most of microwave range

absorbers in the market, seen in the anechoic chamber are made of carbon impregnating polyurethane foam or polystyrene with carbon.

The pyramidal absorber is investigated but for general purpose of EMC application, it includes the suppression of electromagnetic echoes from the flat reflecting surfaces other than chamber walls. To date, no study has been conducted to investigate the effectiveness of flat planar of sugarcane bagasse (SCB) and rubber tire dust (RTD) based microwave absorber as it has robust design and wide electromagnetic application. The absorber material that configures line inside the floor of the shielded room is magnetic loss ferrite tile which is suitable for low frequencies within the range of 30MHz to 1000MHz. The drawback of this material is that it is not suitable for high frequencies (R. Walker, F. Leuterer, D. Wagner & Hailer, 2002).

The most important point in the optimization of designing the EMC absorber is the information regarding the behavior of the dielectric properties of the materials. To date, no detailed data are available for the sugarcane bagasse and rubber tire dust in a broad frequency range of 1GHz to 20 GHz especially in the composition between those two materials. So, in this thesis the thorough information of the dielectric behavior of the materials are investigated and explained. The electromagnetic wave absorbed by a material is related to the dielectric properties of the material and the design of the absorber. Dielectric properties are functions of frequency and consequently the absorbing properties vary significantly as the frequency varied.

1.4 Objectives of Project

The main objective of the project is to design and fabricate the pyramidal microwave absorbers composed of waste material which is sugarcane bagasse for the potential used in EMC- oriented application. In order to enhance the performance, the rubber tire dust has been added as the addition filler. The process of designing and fabricating the microwave absorbers depend upon many factors including electromagnetic dielectric properties, shape, propagation constant, and frequency of the incident wave. The overall objectives of this research are:

- 1 To characterize new composite materials between the sugarcane bagasse (SCB) and rubber tire dust (RTD) by measuring the dielectric properties of the new materials in the broad frequency range of 1.0 GHz to 20 GHz.
- 2 To evaluate the effectiveness of the SCB material in suppressing and absorbing the electromagnetic echoes lower than -20 dB by using layer and multilayer design
- 3 To enhance the microwave absorption by designing and developing sugarcane bagasse (SCB) and rubber tire dust (RTD) microwave absorber using pyramidal shape.

1.5 Scopes of Project

To achieve the objectives of the study, the scopes of this project included design and develop the microwave absorbers using sugarcane bagasse. Experiments will be performed to test the performance (reflectivity and transmission coefficient) and the dielectric properties of the microwave absorbers. The sugarcane bagasse is also being composited with rubber tire dust. The scope of this project includes: