



**PHOTOVOLTAIC POWERED UNINTERRUPTED POWER SUPPLY  
BASED ON PIC MICROCONTROLLER**

by

**MAHRIZAL MASRI  
(0840210254)**

A thesis submitted in fulfillment of the requirements for the degree of  
Doctor of Philosophy

**School of Computer and Communication Engineering  
UNIVERSITI MALAYSIA PERLIS  
2015**

## ACKNOWLEDGMENT

Alhamdulillah, thankful to Allah for giving me the strength and patience to complete my research. This research project would not have possible without the support of many people. First, I wish to express my gratitude to my supervisor and co-supervisor, Prof. Dr. R. Badlishah Bin Ahmad and Dr. Muhammad Irwanto who were abundantly helpful and offered invaluable assistance, support and guidance. Deepest gratitude also to the members of the supervisory committee, Dr. Gomesh Nair a/l Shashidaran, Dr. Mohd Irwan Yusoff whose knowledge and assistance this study would not have been successful.

Special thanks to all my graduate friends, especially members of Centre of Excellence for Renewable Energy (CERE) and technician team for sharing the literature and invaluable assistance.

I am very grateful to school of Computer and Telecommunication Engineering, Universiti Malaysia Perlis for its support of equipment towards accomplishment of this study.

Last but not least, I wish to express my love and gratitude to my beloved families, for their understanding and endless love, through the duration of my studies.

## TABLE OF CONTENTS

<b>DECLARATION OF THESIS</b>	<b>i</b>
<b>ACKNOWLEDGMENT</b>	<b>ii</b>
<b>TABLE OF CONTENTS</b>	<b>iii</b>
<b>LIST OF TABLE</b>	<b>vii</b>
<b>LIST OF FIGURE</b>	<b>viii</b>
<b>LIST OF ABBREVIATION</b>	<b>xiv</b>
<b>LIST OF SYMBOLS</b>	<b>xv</b>
<b>ABSTRAK</b>	<b>xvii</b>
<b>ABSTRACT</b>	<b>xviii</b>
<b>CHAPTER 1 INTRODUCTION</b>	
1.1 Background	1
1.2 Problem Statement	3
1.3 Objectives	5
1.4 Thesis Scope	6
1.5 Thesis Organization	7

## **CHAPTER 2 LITERATURE REVIEW**

2.1 Introduction	9
2.2 Solar Irradiation Potential	11
2.3 Effect of Solar Irradiance and Temperature on Photovoltaic Module Performance	15
2.4 Battery Charger	18
2.4.1 Battery Charger with AC Source as Main Energy Source	19
2.4.2 Battery Charger with Energy Source from Renewable Energy	23
2.5 Uninterrupted Power Supply	28
2.5.1 Transfer Switch Technique of Uninterrupted Power Supply	30
2.5.2 Harmonic Content on Single Phase Inverter	35
2.6 Summary	40

## **CHAPTER 3 RESEARCH METHODOLOGY**

3.1 Research Framework	41
3.2 Solar Irradiation Potential	44
3.2.1 Data Collection of Solar irradiation and Temperature	45
3.2.2 Solar Irradiation Throughout Year 2011 to 2013	49
3.3 PV Module	53
3.3.1 Effect of Temperature and Solar Irradiation on the Performance of PV Module	54
3.3.2 Measurement of the PV Module Performance	58
3.3.3 Simulation and Measurement Validation of the PV Module	

Performance	59
3.4 Optimum Sizing of Photovoltaic Powered UPS System	63
3.5 Three Level Single Phase PV Powered UPS System	64
3.5.1 Solar Charger	65
3.5.2 Transfer Switch Controlled by PIC Microcontroller	67
3.5.3 Single Phase Inverter	68
3.5.4 Operation Principle of Topology of AC Three Level Waveform	73
3.5.5 Harmonic Reduction Technique of Three level Single Phase PV Powered UPS System	77
3.5.6 Printed Circuit Board Design of Three Level Single Phase PV Powered UPS System	78
3.5.7 Assemble Three Level Single Phase PV Powered UPS System	90
3.5.8 Procedure to Control Solar Charger and Produce an AC Three level Single Phase Voltage Waveform	93
3.6 Experimental Setup of Photovoltaic Powered UPS System	94

## **CHAPTER 4 RESULTS AND DISCUSSION**

4.1 Solar Irradiation Potential As Energy Source of Photovoltaic Powered Uninterrupted Power Supply	98
4.1.1 Daily Solar Irradiation	98
4.1.2 Monthly Solar Irradiation	101
4.1.3 PV Power Generation Capacity	103

4.2	Performance of Photovoltaic Module	104
4.2.1	Solar Irradiation and Temperature Effect on the Photovoltaic Module Performance	104
4.2.2	3-Dimensional Diagram of PV Module Performance as Function of Both Solar irradiation and temperature	108
4.2.3	Measurement and Simulation Validation of PV Module Performance	112
4.3	Optimum Sizing of Photovoltaic Powered UPS System	115
4.4	Three-Level AC Voltage and Current Waveform on the PV Powered UPS System	116
4.5	Peak voltage angle Effect on The Performance of PV Powered UPS System	121
4.6	Reduction Technique of Current Total Harmonic Distortion on Three Level Single Phase PV Powered UPS System	130
4.7	Charging Condition of PV Powered UPS System	137
4.8	Comparison of Square and Three-Level Single Phase PV Powered UPS System	142
4.8.1	Temperature, Solar Irradiation and PV Module Output Voltage	142
4.8.2	Current and Voltage Waveform of Square and Three-Level Single Phase PV Powered UPS System	146
4.8.3	Current Total Harmonic Distortion (CTHD)	150
4.9	Comparative Study between Proposed Three-level Single Phase PV Powered UPS System and Market Three-level Inverter	153
4.10	AC Voltage Waveform on The Change Over of Transfer Switch	158

## **CHAPTER 5 CONCLUSION AND RECOMMENDATION**

5.1	Conclusion	161
5.2	Recommendation and Future Work	162

©This item is protected by original copyright

## LIST OF FIGURES

NO.		PAGE
2.1	Battery charger system proposed by Tsang & Chan (2009), (2011)	20
2.2	Circuit diagram of battery charger proposed by & Zhao (2011)	21
2.3	Block diagram of battery charger proposed by Al-kaabi et al. (2013)	22
2.4	Battery charger system based on a contactless energy-transfer circuit proposed by Huang et al. (2013)	23
2.5	Thermoelectric battery charger system proposed by Eakburanawat & Boonyaroonate (2006)	25
2.6	Solar battery charger system proposed by Karami et al., 2012	26
2.7	Solar battery charger system proposed by Nguyen et al. (2013)	27
2.8	Block diagram of stand by UPS	30
2.9	Block diagram of hybrid UPS	32
2.10	Block diagram of online UPS	33
2.11	A simplest power switching schematic of full-bridge inverter	36
2.12	Square wave output voltage of the full-bridge inverter	36
2.13	Three-level waveform generated by the full-bridge inverter	37
2.14	Inverter efficiency versus maximum voltage angle	38
3.1	Research framework for Photovoltaic Powered UPS System	43
3.2	REEC Station in Kangar, Perlis, Northern Malaysia	46
3.3	Installation of Vantage Weather Station Pro2	46
3.4	Methodology of solar irradiation data collection and analysis throughout year 2011 to 2013	51
3.5	Steps of analysis of temperature and solar irradiation change effect on performance of PV module	57
3.6	Measurement of PV module performance	58

## LIST OF TABLES

NO.		PAGE
3.1	Electricity parameters of 21 V, 62 W UNI SOLAR PV module	53
3.2	The required data to optimize the sizing of PV powered UPS system	63
3.3	Zero and peak voltage angle, $\beta$ and $\alpha$	78
4.1	Minimum, maximum and mean solar irradiation through the year of 2011 to 2013	99
4.2	Number of day and their percentage of the solar irradiations for below 1 kWh/m <sup>2</sup> , 1 kWh/m <sup>2</sup> to 3 kWh/m <sup>2</sup> and above 3 kWh/m <sup>2</sup> for year 2011 to 2013	101
4.3	PV module performance at different solar irradiation and temperature	108
4.4	Statistical analysis of Measurement and validation of PV Module Performance	114
4.5	Charging condition of PV powered UPS system for 12 V, 100 Ah RITAR battery	140
4.6	Charging condition of PV powered UPS system for 12 V, 7.5 Ah POWERBATT battery	141
4.7	Maximum, minimum and mean of the solar irradiation and temperature	144
4.8	Maximum, minimum and mean of the AC load rms current and voltage of the square and three-level single phase PV powered UPS system recorded every five minutes	150
4.9	CTHD of the square and three level single phase PV powered UPS system recorded every five minutes	152
4.10	CTHD of the inverters and reduction percentage of CTHD of the proposed three-level single phase PV powered UPS system compared the others	158

## LIST OF ABBREVIATION

AC	Alternating Current
CERE	Centre of Excellence for Renewable Energy
CRM	Coefficient of Residual Mass
CTHD	Current Total Harmonic Distortion
DC	Direct Current
NSE	Nash-Sutcliffe equation
PCB	Printed Circuit Board
PIC	Peripheral Interface Controller
PSHs	Peak Sun Hours
PV	Photovoltaic
RMSE	Root Mean Squared Error
STC	Standard Test Condition for PV module
TNB	Tenaga Nasional Berhad
UPS	Uninterrupted Power Supply

## LIST OF SYMBOLS

$A$	An “apparent” extraterrestrial flux
$A_i$	Area of orientation surface, i
$e$	Percentage error
$E_{out}$	Total Electricity Energy
$E_{solar, i}$	Available solar radiation on different orientation surfaces
$f$	Utilization factor
$I_{SC}$	Short circuit current of PV module
$I_{max}$	Maximum current of PV module
$I_{MPP}$	Current of PV module in the maximum power point STC
$I(\alpha, T, V)$	The circuit current as function of solar irradiance, temperature
$J_s$	The saturation current density
$k$	Optical depth
$P_{max}$	Maximum power of PV module
$P_{mea}$	The measured power of PV module
$P_{MPP}$	Maximum Power Point
$P_{sim}$	The simulated power of PV module
$R_s$	Solar radiation

$R_a$	Extraterrestrial radiation
$T_d$	Difference between maximum and minimum air temperature
$T_N$	Nominal temperature (25 °C)
$TC_i$	Temperature coefficients of the short circuit current of PV module
$TC_v$	Temperature coefficients of the open circuit voltage of PV module
$V_{OC}$	Open circuit voltage of PV module
$V_{\min}$	Minimum voltage of PV module
$V_{\max}$	Maximum voltage of PV module
$V_{MPP}$	Voltage of PV module in the maximum power point STC
$V_{oc}(\alpha, T)$	The open circuit voltage as function of solar irradiance and temperature
$V_{rms}$	rms value of the voltage waveform generated
$\beta$	Zero voltage angle of three level AC waveform
$\eta_{pv}$	Efficiency of PV modules
$\alpha$	Maximum voltage angle of three level AC waveform
$\alpha_{\min}$	Minimum solar irradiance
$\alpha_{\max}$	Maximum solar irradiance
$\tau$	The minority lifetime

3.7	Steps of simulation and measurement validation of PV module power	62
3.8	Block diagram at proposed single phase PV powered UPS system	64
3.9	Circuit of solar charger for charging battery	65
3.10	Circuit of transfer switch for changing main power and inverter source	67
3.11	Pulse and three level output waveform of the single phase PV powered UPS system	71
3.12	Pulse and three-level output waveform of the single phase high switching frequency transformer inverter	72
3.13	Two complete operation modes of proposed single phase inverter	75
3.14	Pulse and three-level output waveform of the AC three-level waveform	76
3.15	Block diagram of design of three-level single phase PV powered UPS system	79
3.16	Solar charger controller schematic of the three-level single phase PV powered UPS system	80
3.17	Transfer switch schematic of the three-level single phase PV powered UPS system	80
3.18	Three-level single phase inverter schematic of the three-level single phase PV powered UPS system	
	(a) : Pulse driver	81
	(b) : Half Bridge	81
	(c) : Full Bridge	82
	(d) : Rectifier	82
3.19	Solar charger controller lay out and 3D visualization of the three-level single phase PV powered UPS system	83
3.20	Transfer switch lay out and 3D visualization of the three-level single phase PV powered UPS system	84
3.21	Three-level single phase inverter lay out and 3D visualization of the three-level single phase PV powered UPS system	
	(a) : Pulse driver	84

	(b) : Half bridge	85
	(c) : Full bridge	85
	(d) : Rectifier	86
3.22	PCB and components of solar charger controller of the three-level single phase PV powered UPS system	
	(a) : 30 A solar charger	87
	(b) : Charger controller	87
3.23	PCB and components of transfer switch of the three-level single phase PV powered UPS system	88
3.24	PCB and components of the three-level single phase PV powered UPS system	
	(a) : Pulse driver	88
	(b) : Half bridge	89
	(c) : Full bridge	89
	(d) : Rectifier	90
3.25	Assemble three-level single PV proposed UPS system in a box	
	(a) : Top view of PV powered UPS system	91
	(b) : Side view of PV powered UPS system	91
	(c) : In front view of PV powered UPS system	92
	(d) : Behind view of PV powered UPS system	92
3.26	Block diagram of experimental setup	94
3.27	PV array for Generating DC Electrical source	95
3.28	Experimental setup of three-level single phase PV powered UPS system	96
3.29	Steps of design and experimental set up of three level single phase PV powered UPS system	97
4.1	Daily solar irradiations during the year of 2011 to 2013	99
4.2	Daily solar irradiation distribution for year 2011, 2012 and 2013	100
4.3	Monthly mean solar irradiation from year 2011 to 2013	102
4.4	Peak sun hours (PSHs) from year 2011 to 2013	102
4.5	Solar irradiation effect on the PV module performance	
	(a) : Curve of short circuit current against open circuit voltage	106
	(b) : Curve of power against open circuit voltage	106

4.6	Temperature effect on the PV module performance	
	(a) : Curve of short circuit current against open circuit voltage	107
	(b) : Curve of power against open circuit voltage	107
4.7	PV module short circuit current as function of both solar irradiation and temperature	109
4.8	PV module maximum peak point current as function of both solar irradiation and temperature	109
4.9	PV module maximum peak point voltage as function of both solar irradiation and temperature	110
4.10	PV module maximum power as function of both solar irradiation and temperature	111
4.11	PV module maximum power as function of both solar irradiation and temperature	111
4.12	Model of short circuit current versus PV module open circuit voltage for the solar irradiation of $727 \text{ W/m}^2$ and temperature of $35^\circ\text{C}$	112
4.13	Simulation result of power versus PV module open circuit voltage for the solar irradiation of $727 \text{ W/m}^2$ and temperature of $35^\circ\text{C}$	113
4.14	Measurement result of power versus PV module open circuit voltage for the solar irradiation of $727 \text{ W/m}^2$ and temperature of $35^\circ\text{C}$	113
4.15.	Simulation output result of PV module and battery optimum sizing	115
4.16	Block diagram of optimum sizing of PV powered UPS system	116
4.17	Pulse wave produced by the pin 7, 8, 9 and 10 of PIC16F628A-I/P	117
4.18	AC square waveform on the transformer secondary winding	118
4.19	Root mean square voltage on the transformer secondary winding	118
4.20	Pulse wave produced by the pin 1 and 2 of PIC16F628A-I/P	119
4.21	AC three-level waveform on the full bridge circuit output	120
4.22	Root mean square voltage on the full bridge circuit output	120

4.23	Changes of pulse wave to develop changes of peak voltage angle	123
4.24	AC current and voltage waveform of the PV powered UPS system on the different peak voltage angles	126
4.25	Peak voltage angle effect on the rms AC voltage and current	128
4.26	Peak voltage angle effect on the AC power	128
4.27	AC voltage and current waveform for varies load	129
4.28	Peak voltage angle effect on PV powered UPS system on the different peak voltage angle	134
4.29	Peak voltage angle effect on current total harmonic distortion (CTHD)	136
4.30	Charging condition of PV powered UPS system	137
4.31	Solar irradiation and temperature for the charging condition of PV powered	
	(a) : 12 V, 100 Ah RITAR battery	138
	(b) : 12 V, 7,5 Ah POWERBATT battery	138
4.32	PV and battery voltage, also charging current of PV powered UPS system	
	(a) : 12 V, 100 Ah RITAR battery	139
	(b) : 12 V, 7,5 Ah POWERBATT battery	139
4.33	Fully charging condition of PV powered UPS system	141
4.34	Solar irradiation on 12 <sup>th</sup> December 2014 and 13 <sup>th</sup> December 2014	143
4.35	Temperature on 12 <sup>th</sup> December 2014 and 13 <sup>th</sup> December 2014	143
4.36	Output voltage of PV array	144
4.37	Battery voltage in charging condition	145
4.38	Charging current	146
4.39	AC load current and voltage waveform of the single phase PV powered UPS system	
	(a) : Square wave	147
	(b) : Three-level waveform	148

4.40	AC load rms current and voltage of the square and three-level single phase PV powered UPS system recorded every minute	
	(a) : AC load rms voltage	149
	(b) : AC load current	149
4.41	Current harmonic spectrum of the single phase inverter of PV powered UPS system	
	(a) : Square wave	151
	(b) : Three-level waveform	151
4.42	Current total harmonic distortion (CTHD) of the square and three-level single phase PV powered UPS system recorded every five minutes	152
4.43	AC load performance of PV powered UPS system	
	(a) : Voltage and current waveform	154
	(b) : Spectrum of current harmonic	154
4.44	AC load performance of 2000 W power inverter	
	(a) : Voltage and current waveform	155
	(b) : Spectrum of current harmonic	155
4.45	AC load performance of 2000 W Charger 10A SUVPR Series DY 2000C	
	(a) : Voltage and current waveform	156
	(b) : Spectrum of current harmonic	156
4.46	AC load performance of 1000 W Charger 10A SUVPR Series DY 1000C	
	(a) : Voltage and current waveform	157
	(b) : Spectrum of current harmonic	157
4.47	AC voltage waveform on the change over of transfer switch	
	(a) From main power source (TNB) to PV powered UPS system	159
	(b) From PV powered UPS system to main power source (TNB)	160

## Bekalan Kuasa Tanpa Gangguan dikuasakan Fotovolta Yang Diasaskan Pada PIC Mikropengawal

### ABSTRAK

Tesis ini mengemukakan sistem bekalan kuasa tanpa gangguan dikuasakan fotovolta yang menggunakan PIC mikropengawal. Kajian upaya sinaran suria adalah amat penting untuk mengetahui upayanya guna membina sistem bekalan kuasa tanpa gangguan dikuasakan fotovolta. Sistem bekalan kuasa tanpa gangguan dikuasakan fotovolta tersebut harus memiliki satu pengecas suria yang boleh cas bateri dengan cepat, satu suis pindah ambil-alih yang memenuhi piawai IEC 62040-3 dan satu penyongsang yang memiliki herotan harmonik jumlah arus (CTHD) terendah. Untuk alasan-alasan ini, objektif-objektif tesis ini adalah untuk menganalisis keupayaan sinaran suria guna membina sistem bekalan kuasa tanpa gangguan dikuasakan fotovolta, untuk merekabentuk satu pengecas suria, satu suis pindahan dan satu penyongsang. Data upaya sinaran suria diukur pada Stesen Pusat Kecemerlangan untuk Tenaga Boleh Diperbaharui, Universiti Malaysia Perlis di Kangar, Perlis, Malaysia Belahan Utara. Pengecas suria, suis pindah dan penyongsang dibina oleh PIC mikropengawal. Hasil-hasil menunjukkan bahawa sinaran suria bulanan ialah  $4824.81 \text{ Wh/m}^2$ . Ianya lebih besar dari  $3000 \text{ Wh/m}^2$  dan menunjukkan bahawa langit di Perlis cerah dan keamatan sinaran suria potensi sangat tinggi. Ianya menunjukkan bahawa sinaran suria di Perlis memberikan upaya yang besar untuk sistem bekalan kuasa tanpa gangguan fotovolta. Pengecas suria yang dicadangkan boleh menghantarkan arus pengecasan sehingga 20 A. Ini kerana arus tersebut boleh dibagi dalam nilai yang sama oleh litar arus berbilang. Teknik penyongsang yang dicadangkan boleh merubah sudut voltan maksimum dari bentuk gelombang tiga aras dari  $20^\circ$  sampai  $180^\circ$ . Satu beban ulang alik yang dikenakan ke penyongsang dikuasakan fotovolta menunjukkan bahawa herotan harmonic jumlah arus terendah (CTHD) diperolehi ketika sudut voltan maksimum adalah  $134^\circ$ . Satu kajian perbandingan (CTHD) antara penyongsang fotovolta tanpa pengubah satu fasa tiga aras dan penyongsang tiga aras pasaran (2000 W power inverter, 2000 W Charger 10A SUVPR Series DY 2000C and 1000 W Charger 10A SUVPR Series DY 1000C) juga telah dilakukan. Hasil tersebut menunjukkan bahawa CTHD dari penyongsang fotovolta tanpa pengubah satu fasa tiga aras lebih rendah berbanding CTHD dari penyongsang-penyongsang tiga aras pasaran.

## Photovoltaic Powered Uninterrupted Power Supply Based on PIC Microcontroller

### ABSTRACT

This thesis presents the photovoltaic (PV) powered uninterrupted power supply (UPS) system based on PIC microcontroller. The study of solar radiation is very important to know its potential to develop the PV powered UPS system. The PV powered UPS system should have a solar charger that can charge the battery fast, a change over of transfer switch that fulfill the standard of IEC 62040-3 and an inverter that has a lowest current total harmonic distortion (CTHD). For these reasons, the thesis objectives are to analyze the solar radiation potential to develop PV powered UPS system, to design a solar charger, a transfer switch and an inverter. The data of solar radiation are measured at the Renewable Energy Excellence Centre (REEC) Station, Universiti Malaysia Perlis in Kangar, Perlis, Northern Malaysia. The solar charger, transfer switch and inverter are constructed by PIC microcontroller. The results show that the average monthly solar radiation is 4824.81 Wh/m<sup>2</sup>. It is greater than 3000 Wh/m<sup>2</sup> and indicates that the sky in Perlis is clear and the solar radiation intensity is very high. It indicates that the solar radiation in Perlis gives big potential for PV powered UPS system. The proposed solar charger can flow the charging current up to 24 A. It is due to the current can be divided in same value by the multiple current circuits. The proposed inverter technique is able to change peak voltage angle of the AC three-level waveform from 20<sup>0</sup> to 180<sup>0</sup>. An AC load applied to the PV powered inverter shows that the lowest CTHD is obtained when the peak voltage angle is 134<sup>0</sup>. A comparative study of CTHD between the proposed three level single phase PV inverter and the market three level inverters (2000 W power inverter, 2000 W Charger 10A SUVPR Series DY 2000C and 1000 W Charger 10A SUVPR Series DY 1000C) are conducted. The result shows that the CTHD of proposed three level single phase PV inverter is lower than the CTHD of the market three level inverters.

# CHAPTER 1

## INTRODUCTION

### 1.1 Background

Since the conventional energy reached its crisis, it has given a bad effect on the economical growth and energy demand. Due to the reduction of conventional energy, the transportation and power plant systems that use the fossil fuel can be stopped. The effects have motivated the researchers to find the alternative energy. The renewable energy has been obtained and applied as an alternative energy which produced continuity and it is widely used in the world (Alam & Manfred, 2010).

Solar energy is one part of the renewable energy, it is a fusion process of the sun that produces solar irradiation and reaches the surface of earth. The study of solar irradiation in one area of the earth surface is very important. The daily, monthly and annual data collection of solar irradiation are useful to give information in the one area that it is suitable or not to develop a photovoltaic (PV) power generation. By knowing the area of orientation surface, efficiency and utilization factor of the PV module, thus the annual potential electricity generating capacity from the PV systems for the area can be estimated.

PV performance depends on the solar irradiation and temperature. If the solar irradiation increases and the temperature is constant, thus the PV performance will increase. Inversely, if the temperature increases and the solar irradiation is constant,

thus the PV performance will decrease. The PV performance affects the capability of the charging system in the PV application. A high PV performance will produce a high charging current. It is important to reach the fast fully charging condition of the battery (Hussein & Fardoun, 2014).

The battery charged by the PV can be applied into an uninterrupted power supply (UPS). The UPS is used as a back up power source for emergency electrical loads in case of main power source failure. Usually, it is applied directly from the main power source, until the main power source fails. After the failure, inverter operated by a battery will turn on to supply electric power to the electrical loads. The battery is charged when main power source is available. The life time of the inverter depends on the battery capacity. The battery powered inverter is charged by the main power source can not be applied in the rural area.

Normally, the inverter is constructed by some switching electronic components. The components decide the output voltage waveform of the inverter. It will produce harmonic and affects the life time of the electrical loads. If the harmonic of the inverter is poor, thus the life time of the electrical loads are long. Inversely, if the harmonic of the inverter is reach, thus the life time of the electrical loads are shorten. A harmonic reduction technique of the inverter is important to be studied. The general technique is how to drive the switching electronic components and produce the output voltage waveform of the inverter with poor harmonic.

This thesis presents the daily, monthly and annual solar irradiation in Perlis. They are observed and analyzed to obtain the potential of PV powered UPS system

application. A PV powered UPS system using PIC microcontroller is developed. It is a backup UPS whereas if the main power source fails to supply power to the electrical loads, inverter operated by a battery will turn on to supply electric power continuously. The PV module charges the battery using solar charger and the transfer switch is controlled by PIC microcontroller.

## 1.2 Problem Statement

In this thesis, the problem statements are stated as below:

1. The solar irradiation data are the most important component to estimate output of photovoltaic systems. The information of daily, monthly and annual solar irradiation are important to know the potential of solar irradiation for PV powered UPS system. Shijun and Hongxing (1997) states that the area requirement should be fulfilled to generate the photovoltaic is that the area has solar irradiation above 3 kWh/m<sup>2</sup>. Markvart (1994), Itagaki et al. (2003) and Mellit et al. (2007) also state that the area has peak sun hours (PSHs) is above 3 hours. Laleman et al., 2011 states that the solar irradiation can be classified into four categorizes. They are low solar irradiation (below 2.6 kWh/m<sup>2</sup>), moderate solar irradiation (between 2.6 – 3 kWh/m<sup>2</sup>), high solar irradiation (between 3-4 kWh/m<sup>2</sup>) and very high solar irradiation (above 4 kWh/m<sup>2</sup>). It is important to know the sky condition and its potential towards PV application, especially the PV powered UPS system in Perlis, Northern Malaysia.

2. UPS system needs batteries to run it. Usually, the battery is charged by the main power source using a rectifier circuit. It means that the UPS only can be operated in the main power source area or it can not be operated in the rural area (no utility grid). A design of UPS completed by solar charger is important in case of its application. It can be operated in both of the main power source area and also the rural area. The batteries are charged by PV module using solar charger. A higher current of the solar charger will charge the batteries fast. Karami et al., 2012 states that the power consumed by the batteries is related to their states of charge (SOC) which is charged by PV module. The PV current at different solar irradiance should be compatible with charging current required to charge the batteries. A critical situation occurs at high solar irradiance when the PV module delivers a high current that exceeds the tolerated charging current. If it is not controlled, the batteries can be damaged. In this case, a design of solar charger controller is important to maintain the batteries safety condition.
3. UPS system needs a transfer switch to transfer electrical energy from failed main power source to inverter source. The transfer switch needs high speed accuracy to detect the failed main power source. Normally, the transfer switch is developed by static transfer switch, it is DC relay (Alam et al, 2013). It has lower speed accuracy compared to the PIC microcontroller. Thus, it is very important to develop a transfer switch in the Photovoltaic powered UPS system which has high speed accuracy.
4. Inverters installed in the UPS system are developed by using electronic components which produce harmonic. The simplest technique to invert DC power into AC power is to generate a square wave. However, not only the harmonic content of the square

wave is relatively high, but also the efficiency of this waveform is relatively low. Anis, 1988, 1992; Daut, et al., 2012; Irwanto et al., 2013 states that in term harmonic shows that three-level AC waveform is better than AC square waveform. An AC three-level waveform consists of maximum and minimum voltage angle created by the switching electronic components. A design of driver circuit to drive the switching electronic components is needed to obtain an optimum maximum voltage angle that related to the lowest current total harmonic distortion (CTHD). The lowest CTHD will give a longer life time of the electrical loads.

### 1.3 Objectives

The objectives of this study are ;

1. To analyze the daily, monthly and annual solar irradiation in Perlis, Northern Malaysia as potential to generate PV powered UPS system.
2. To design a solar charger in the PV powered UPS system using PIC microcontroller which can be operated in both of the main power source area and also the rural area, it can flow high current and charge the battery fast.
3. To design a transfer switch in the PV powered UPS system using PIC microcontroller which has high speed accuracy.